# Intrinsically Safe Explosion-proof System **5 Port Solenoid Valve**

Can be used as a certified intrinsic safety type product only in Japan.


# Exia II BT4 (TIIS approved product)

This product has been certified as an intrinsic safety type system consisting of an electromagnet for a solenoid valve in combination with a safety retainer, for type approval as an explosion proof electric apparatus by Technology Institution of Industrial Safety (TIIS).





# Compact, High Flow



### Dimensions

Dimension Model	L1	L2	L3	
51-SY5120-L	40 -	104		
51-SY5120-LL		104	15	
51-SY5120-TT		120.8		
51-SY7120-L		118.2		
51-SY7120-LL			18	
51-SY7120-TT		135		
51-SY9120-L		148.3		
51-SY9120-LL		140.3	23	
51-SY9120-TT		165.1		

### **Flow-rate Characteristics**

		Flow-rate characteristics						
Ser	ies	1→4/2	(P→A/E	3)	4/2→5/3 (A/B→EA/EB)			
		C[dm <sup>3</sup> /(s·bar)]	b	Cv	C[dm <sup>3</sup> /(s·bar)]	b	Cv	
	51-SY5 <u>□</u> 20	1.9	0.35	0.49	2.4	0.39	0.61	
Body ported	51-SY7 <u>□</u> 20	4.1	0.23	0.93	3.3	0.33	0.81	
	51-SY9 <u>□</u> 20	7.0	0.33	1.7	7.6	0.35	2.0	
	51-SY5∐40	2.4	0.41	0.64	2.8	0.29	0.66	
Base mounted	51-SY7∐40	4.1	0.41	1.1	4.1	0.29	1.0	
	51-SY9 <u></u> 40	7.9	0.34	2.0	9.6	0.43	2.6	




# 3 Types of Connectors Easily maintained by adapting connector for the lead wire (L- and LL-type) L-type plug connector (L-type) L-type plug connector with cover (LL-type) With IP65 compliant cable (TT-type)





# **Intrinsically Safe Explosion-proof System** 5 Port Solenoid Valve Series 51-SY5000/7000/9000 **Body Ported Single Unit**

### **How to Order**



Note) TT-type is connected to the terminal block. Cables other than the connected one cannot be used.



# Body Ported *Series* 51-SY5000/7000/9000



### **Specifications**

S	Series	51-SY5000	51-SY7000	51-SY9000		
Fluid			Air			
Internal pilot	2-position single		0.15 to 0.7			
operating pressure	2-position double		0.1 to 0.7			
range (MPa)	3-position	0.2 to 0.7				
Ambient and fluid t	emperature (°C)	-10	to 50 (No freezi	ing)		
Max. operating	2-position single, double		1			
frequency (Hz)	frequency (Hz) 3-position		<b>I</b>			
Manual override (M	lanual operation)	Non-locking push type, Push-turn locking slotted type, Push-turn locking lever type				
Pilot exhaust meth	od	Main/Pilot valve common exhaust				
Lubrication		Not required				
Mounting orientation	on	Unrestricted				
Impact/Vibration re	sistance (m/s²) Note)	150/30				
Enclosure		IP30 (L-type), IP40 (LL-type), IP65 (TT-type)				

\* Based on IEC60529 Note) Impact resistance:

Note) Impact resistance: No malfunction occurred when it is tested in the axial direction and at the right angles to the main valve and armature in both energized and de-energized states every once for each condition. (Values at the initial period)

Vibration resistance: No malfunction occurred in a one-sweep test between 45 and 2000 Hz. Test was performed at both energized and de-energized states in the axial direction and at the right angles to the main valve and armature. (Values at the initial period)

### **Solenoid Specifications**

Electrical entry	L-type plug connector (L), L-type plug connector with cover (LL), With IP65 compliant cable (TT)
Coil rated voltage	12 VDC
Allowable voltage fluctuation	-10% to +10% of rated voltage
Coil insulation type	Class B
Power consumption	0.52 W (at rated voltage)

### **Intrinsically Safe Explosion-proof System Specifications**

Type of explosion-proof structure	Intrinsically safe explosion-proof structure (ia) Note 1)		
Applicable gas or ignition temperature of steam and explosion class	IIBT4		
Voltage to barrier	24 VDC (rated voltage of system) Note 2) Note 3)		
Tolerant voltage fluctuation	Refer to the barrier dimensions on page 41 and 42.		

Note 1) **Marning** Can not be used in a class-0 environment. Use in a class-2 or class-1 environment.

Note 2) **Caution** The valve and barrier have polarity. If voltage is supplied with wrong polarity, the barrier can not be used.

Note 3) **Caution** Voltage to the valve should be 10.8 VDC (minimum value).

### Response Time

 $\bigcirc$ 

Note) Based on dynamic performance test, JIS B8419: 2010. (Coil temperature: 20°C, system A, F at 24 VDC)

Type of actuation	Response time (ms) (at 0.5 MPa)					
Type of actuation	51-SY5000	51-SY7000	51-SY9000			
2-position single	26 or less	38 or less	50 or less			
2-position double	22 or less	30 or less	50 or less			
3-position	38 or less	56 or less	_			



### **Flow-rate Characteristics**


### **Series 51-SY5000**

Jeries		0130	Port	size	Flo	w-rate	e char	acteri	stics N	lote)
Valve	Ty	pe of				2 (P-			3 (A/B→	
model		tuation	1, 5, 3 (P, EA, EB)	4, 2 (A, B)	C(dm³/ (s·bar))	b	Cv	C(dm³/ (s·bar))	b	Cv
	2- position	Single Double			1.9	0.35	0.49	2.4	0.39	0.61
51-SY5 □20-□		Closed center		1/8	1.7	0.43	0.45	1.8	0.35	0.46
-01	3- position	Exhaust center		1/6	1.5	0.44	0.41	2.5 [1.5]	0.32 [0.43]	0.59 [0.40]
		Pressure center			2.2 [0.91]	0.46 [0.58]	0.61 [0.28]	1.8	0.38	0.46
	2- position	Single Double		C4	0.75	0.43	0.20	0.85	0.64	0.30
51-SY5 □20-□		Closed center		ø4 one-	0.74	0.40	0.19	0.84	0.57	0.28
-C4	3- position	Exhaust center		touch fitting/	0.75	0.36	0.19	0.84 [0.84]	0.64 [0.53]	0.30 [0.27]
		Pressure center	1/8		0.78 [0.71]	0.44 [0.37]	0.21 [0.18]	0.84	0.57	0.27
	2- position	Single Double	1/6	C6	1.5	0.33	0.33	2.0	0.37	0.52
51-SY5 □20-□		Closed center		ø6 one-	1.3	0.31	0.33	1.6	0.32	0.39
-C6	3- position	Exhaust center		touch	1.3	0.33	0.33	1.8 [1.4]	0.35 [0.37]	0.44 [0.35]
		Pressure center		\ -/	1.7 [0.80]	0.31 [0.47]	0.42 [0.23]	1.7	0.33	0.44
	2- position	Single Double		<b>C</b> 0	1.9	0.21	0.45	2.3	0.29	0.57
51-SY5		Closed		C8 / ø8 one-	1.6	0.29	0.39	1.7	0.38	0.46
□20-□ -C8	3- position	Exhaust center	st tou	touch	1.4	0.38	0.39	2.0 [1.5]	0.37 [0.41]	0.52 [0.43]
		Pressure center		. 9/	2.2 [1.6]	0.32 [0.44]	0.56 [0.44]	1.8	0.41	0.50

# Note) [ ]: Normal position

### **Series 51-SY7000**

			Port	size	Flo	w-rat	e char	acteri	stics <sup>N</sup>	lote)			
Valve	_ ,	pe of 1, 5, 3		4, 2		/2 (P-	→A/B)	4/2→5/	/3 (A/B→	EA/EB)			
model	act	tuation	(P, EA, EB)	(A, B)	C(dm <sup>3</sup> / (s·bar))	b	Cv	C(dm <sup>3</sup> / (s·bar))	b	Cv			
	2- position	Single Double			4.1	0.23	0.93	3.3	0.33	0.81			
51-SY7 □20-□		Closed center		1/4	2.9	0.31	0.70	2.4	0.38	0.63			
-02	3- position	Exhaust center		1/4	2.5	0.39	0.65	3.4 [2.1]	0.35	0.82 [0.54]			
		Pressure center			4.3 [2.4]	0.23 [0.32]	0.97 [0.61]	2.2	0.39	0.58			
	2- position	Single Double	1 (P)		` .'	C8	3.2	0.26	0.77	3.2	0.37	0.82	
51-SY7	Closed 1/4 / Ø8 \		2.6	0.24	0.63	2.4	0.31	0.62					
□20-□ -C8	3- position	Exhaust center	5, 3 (EA, EB)	5, 3 touch	2.4	0.25	0.57	2.6 [1.9]	0.42 [0.46]	0.70 [0.56]			
		Pressure center			3.3 [2.4]	0.28 [0.22]	0.78 [0.57]	2.2	0.34	0.60			
	2- position	Single Double					C10	3.8	0.26	0.86	3.2	0.34	0.82
51-SY7	1-SY7 □20-□ 3- □ Exhaust center  Pressure center    \$\phi(0)\$   \$	1	2.8	0.27	0.67	2.4	0.21	0.59					
					2.5	0.25	0.59	2.7 [2.0]	0.38 [0.38]	0.70 [0.56]			
				1	3.8 [2.4]	0.25 [0.31]	0.89 [0.61]	2.3	0.38	0.61			





### **Series 51-SY9000**


			Por	t size	Flow-rate characteristics					
Valve	Type of		1, 5, 3	4, 2	1→4	$1 \rightarrow 4/2 (P \rightarrow A/B) \mid 4/2 \rightarrow 5/3 (A/B \rightarrow EA$			EA/EB)	
model	actu	actuation			C(dm <sup>3</sup> / (s·bar))	b	Cv	C(dm <sup>3</sup> / (s·bar))	b	Cv
51-SY9 □20-□	2-	Single		1/4	7.0	0.33	1.7	7.6	0.35	2.0
-02	position	Double		1/4	7.0	0.55	1.7	7.0	0.00	2.0
51-SY9 □20-□	2-	Single		3/8	8.0	0.29	1.9	8.0	0.33	2.0
-03	position	Double		3/6	6.0	0.29	1.9	6.0	0.33	2.0
51-SY9 □20-□	2-	Single		C8 / ø8 one-	4.3	0.28	0.96	7.1	0.32	1.7
-C8	position	Double 1/4	touch fitting/	4.0	0.20	0.50	7.1	0.02	1.7	
51-SY9 □20-□	2-	Single		C10 / ø10 one-	6.1	0.28	1.4	7.9	0.33	1.9
-C10	position	Double		touch fitting/	0.1	0.20	1.4	7.9	0.33	1.9
51-SY9	2-	Double 2-		C12 / ø12 \ one-	7.0	0.25	1.6	8.6	0.41	2.2
□20-□ -C12	nonition	Single		touch fitting/	7.0	0.23	1.0	0.0	0.41	2.2

# Body Ported Series 51-SY5000/7000/9000

### Construction







### **Component Parts**

5 1 3 (EA)(P)(EB)

	mpononi i arto								
No	. Description	Material	Note						
1	Body	Aluminum die-casted	White						
2	Adapter plate	Resin	White (51-SY9000: Gray)						
3	End plate	Resin	White						
4	Piston	Resin	_						
5	Spool valve assembly	alve assembly Aluminum, HNBR							

### **Replacement Parts**

nopiacoment i arte									
No.	Description	Part no.							
6	Port block assembly	Refer to "How to Order Port Block Assembly" on page 5.							


### **Bracket Assembly Part No.**

Description	Part no.
Bracket (for F1)	SX 5000-16-2A (with mounting screw)
Bracket (for F2)	SX 5000-16-1A (with mounting screw)

<sup>\*</sup> The 51-SY9000 has no bracket.


### **How to Change Port Block Assembly**

If using body ported type, both A and B port sizes can be changed by replacing the port block assembly mounted on the body. When changing this block assembly, the correct screw torque must be achieved to avoid possible air leakage.




Mounting screw tightening torques

51-SY<sub>7</sub> 000 (M3): 0.6 N·m 51-SY9000 (M4): 1.4 N·m





### **How to Order Port Block Assembly**



# • A, B port size Thread piping

Symbol	Port size	Applicable series
01	1/8	51-SY5000
02	1/4	51-SY7000
02	1/4	E4 CV0000
03	3/8	51-SY9000

### One-touch fitting (Metric size)

	3( 11 17							
Symbol	Port size	Applicable series						
C4	ø4 one-touch fitting							
C6	ø6 one-touch fitting	51-SY5000						
C8	ø8 one-touch fitting	]						
C8	ø8 one-touch fitting	51-SY7000						
C10	ø10 one-touch fitting	51-517000						
C8	ø8 one-touch fitting							
C10	ø10 one-touch fitting	51-SY9000						
C12	ø12 one-touch fitting							

### One-touch fitting (Inch size)

Symbol	Port size	Applicable series	
N3	ø5/32" one-touch fitting		
N7	ø1/4" one-touch fitting	51-SY5000	
N9	ø5/16" one-touch fitting		
N9	ø5/16" one-touch fitting	51-SY7000	
N11	ø3/8" one-touch fitting	51-517000	
N9	ø5/16" one-touch fitting	51-SY9000	
N11	ø3/8" one-touch fitting	51-519000	


\* Only the fitting assembly replacement is also possible.

### Metric size

ø4 one-touch fitting	VVQ1000-51A-C4		
ø6 one-touch fitting	VVQ1000-51A-C6		
ø8 one-touch fitting	VVQ1000-51A-C8		
ø8 one-touch fitting	VVQ2000-51A-C8		
ø10 one-touch fitting	VVQ2000-51A-C10		
ø8 one-touch fitting	VVQ4000-50B-C8		
ø10 one-touch fitting	VVQ4000-50B-C10		
ø12 one-touch fitting	VVQ4000-50B-C12		
	ø6 one-touch fitting ø8 one-touch fitting ø8 one-touch fitting ø10 one-touch fitting ø8 one-touch fitting ø10 one-touch fitting		

### Inch size


	ø5/32" one-touch fitting	VVQ1000-51A-N3
51-SY5000	ø1/4" one-touch fitting	VVQ1000-51A-N7
	ø5/16" one-touch fitting	VVQ1000-51A-N9
51-SY7000	ø5/16" one-touch fitting	VVQ2000-51A-N9
51-517000	ø3/8" one-touch fitting	VVQ2000-51A-N11
51-SY9000	ø5/16" one-touch fitting	VVQ4000-50B-N9
51-519000	ø3/8" one-touch fitting	VVQ4000-50B-N11




**⚠Warning** If a resin tube is used, take measures against static electricity.

# Body Ported Series 51-SY5000/7000/9000


### Dimensions: 51-SY5000




# With foot bracket 51-SY5120-□L□□-01□-F1




# L-type plug connector with cover (LL) 51-SY5120-□LL□□-01□ (-F2)




# With IP65 compliant cable (TT) 51-SY5120-□TT□□-01□ (-F2)




### Dimensions: 51-SY5000



# L-type plug connector with cover (LL) 51-SY5220-□LL□□-01□ (-F2)




# With IP65 compliant cable (TT) 51-SY5220-□TT□□-01□ (-F2)




# Body Ported Series 51-SY5000/7000/9000


### Dimensions: 51-SY5000




# L-type plug connector with cover (LL) 51-SY5<sup>3</sup>/<sub>4</sub>20-□LL□□-01□ (-F2)




# With IP65 compliant cable (TT) $51-SY5\frac{3}{5}20-\Box TT\Box \Box -01\Box$ (-F2)




### Dimensions: 51-SY7000



# L-type plug connector with cover (LL) 51-SY7120-□LL□□-02□ (-F2)




# With IP65 compliant cable (TT) 51-SY7120-□TT□□-02□ (-F2)




# Body Ported Series 51-SY5000/7000/9000


### Dimensions: 51-SY7000




# L-type plug connector with cover (LL) 51-SY7220-□LL□□-02□ (-F2)




# With IP65 compliant cable (TT) 51-SY7220-□TT□□-02□ (-F2)




### **Dimensions: 51-SY7000**



# L-type plug connector with cover (LL) $51-SY7\frac{3}{4}20-\Box LL\Box\Box -02\Box$ (-F2)




# With IP65 compliant cable (TT) 51-SY7<sup>3</sup>/<sub>2</sub>20-□TT□□-02□ (-F2)




# Body Ported Series 51-SY5000/7000/9000

### Dimensions: 51-SY9000


2-position single L-type plug connector (L) 51-SY9120-□L□□-030



# L-type plug connector with cover (LL) 51-SY9120- $\square$ LL $\square$ - $^{02}_{03}\square$




# With IP65 compliant cable (TT) 51-SY9120- $\Box$ TT $\Box$ - $^{02}_{03}$ $\Box$







### Dimensions: 51-SY9000


2-position double L-type plug connector (L) 51-SY9220-□L□□-032□








# L-type plug connector with cover (LL) 51-SY9220- $\square$ LL $\square$ - $^{02}_{03}\square$



# With IP65 compliant cable (TT) 51-SY9220-□TT□□-03 □



# **Intrinsically Safe Explosion-proof System 5 Port Solenoid Valve** Series 51-SY5000/7000/9000 **Base Mounted**

# **Single Unit**

### **How to Order** 51-SY 5 2 40 Thread type Series • Nil 5 51-SY5000 Port size F G 7 51-SY7000 Symbol Port size Applicable series N **NPT** 51-SY9000 Nil Without sub-plate Т NPTF 51-SY5000 02 Explosion-proof With sub-plate 51-SY7000 Intrinsically safe 51-SY7000 3/8 03 explosion-proof With sub-plate 51-SY9000 structure 1/2 04 51-SY9000 With sub-plate Type of actuation • 2-position single Manual override (A)4 2(B) 1 Nil: Non-locking push D: Push-turn locking E: Push-turn locking slotted type (EA)5 1 3(EB) type lever type 2-position double (A)4 2(B) 2 (EA)513(EB) (P) 3-position closed center (A)4 2(B) 3 Note) (EA)513(EB) (P) Lead wire length 3-position exhaust center Symbol Lead wire length Note (A)4 2(B) ◆Electrical entry 3 300 mm 4 Note) Symbol Electrical entry 6 600 mm Maximum length for L-type (EA)513(EB) (P) 10 1000 mm L-type plug connector 3-position pressure center 15 1500 mm (A)4 2(B) 20 2000 mm 30 3000 mm (EA)513(EB) 100 10000 mm Semi-standard L-type plug connector Note) 3-position type is not available for the 51-SY9000 series LL Pilot type Nil Internal pilot R External pilot With IP65 compliant cable System Note 1) Note 2) Note 3) TT Note)

Z728.H (51-SYE100-A) Α Model certificate number: TC14452 KFD0-SD2-Ex1.1065 (51-SYE100-F) F Model certificate number: TC19711

Note) TT-type is connected to the terminal block. Cables other than the connected one cannot be used.

Note 1) Attached barrier type

The numbers in ( ), 51-SYE100-□ represents SMC's control number.

Note 2) If the barrier is not necessary due to valve replacement etc, enter O after the system symbol. Example) 51-SY5140-AOLL3

Note 3) For this product, the barrier and the valve as a set are certified as a system, so please be aware of the following.

· For this product, both the barrier and the valve have an SMC model certification label with a model certification number listed on it. Be sure to use only a barrier and a valve whose numbers match.


If an SMC model certification label has not been stuck on the product, or if the model certification numbers do not match, the product cannot be said to be an intrinsically safe explosion-proof system. Therefore, be sure to use only a barrier purchased from SMC.





### **Specifications**

	Series		51-SY5000	51-SY7000	51-SY9000	
Fluid			Air			
Internal pilot		2-position single		0.15 to 0.7		
operating pressure range (MPa)		2-position double		0.1 to 0.7		
		3-position	0.2 to 0.7			
External pilot Operating		pressure range	-	-100 kPa to 0.7	7	
operating	Pilot	2-position single		0.25 to 0.7		
pressure range	pressure	2-position double	0.25 to 0.7			
(MPa) range		3-position	0.25 to 0.7			
Ambient and flui	d temperat	ure (°C)	-10 to 50 (No freezing)			
Max. operating	2-pos	ition single, double	1			
frequency (Hz)	3-pos	ition				
Manual override	(Manual op	eration)	Non-locking push type, Push-turn locking slotted type, Push-turn locking lever type			
Pilot exhaust me	thad	Internal pilot	Main/Pilot valve common exhaust			
Pilot extraust file	tillou	External pilot	Pilot valve individual exhaust			
Lubrication			Not required			
Mounting orienta	Mounting orientation			Unrestricted		
Impact/Vibration resistance (m/s²) Note)			150/30			
Enclosure			IP30 (L-type), IP40 (LL-type), IP65 (TT-type)			



Note) Impact resistance: No malfunction occurred when it is tested in the axial direction and at the right angles to the main valve and armature in both energized and de-energized states

every once for each condition. (Values at the initial period)

Vibration resistance: No malfunction occurred in a one-sweep test between 45 and 2000 Hz. Test was performed at both energized and de-energized states in the axial direction and at

performed at both energized and de-energized states in the axial direction and at the right angles to the main valve and armature. (Values at the initial period)

### **Solenoid Specifications**

Electrical entry	L-type plug connector (L), L-type plug connector with cover (LL), With IP65 compliant cable (TT)
Coil rated voltage	12 VDC
Allowable voltage fluctuation	-10% to +10% of rated voltage
Coil insulation type	Class B
Power consumption	0.52 W (at rated voltage)

### **Intrinsically Safe Explosion-proof System Specifications**

Type of explosion-proof structure	Intrinsically safe explosion-proof structure (ia) Note 1)
Applicable gas or ignition temperature of steam and explosion class	IIBT4
Voltage to barrier	24 VDC (rated voltage of system) Note 2) Note 3)
Tolerant voltage fluctuation	Refer to the barrier dimensions on page 41 and 42.

Note 1) **AWarning** Can not be used in a class-0 environment. Use in a class-2 or class-1 environment

Note 2) **Caution** The valve and barrier have polarity. If voltage is supplied with wrong polarity, the barrier can not be used.

Note 3) **Caution** Voltage to the valve should be 10.8 VDC (minimum value).

### **Response Time**



Note) Based on dynamic performance test, JIS B 8375-1981. (Coil temperature: 20°C, system A, F at 24 VDC)

Type of actuation	Response time (ms) (at 0.5 MPa)						
Type of actuation	51-SY5000	51-SY7000	51-SY9000				
2-position single	26 or less	38 or less	50 or less				
2-position double	22 or less	30 or less	50 or less				
3-position	38 or less	56 or less	_				




# Base Mounted Series 51-SY5000/7000/9000

### **Flow-rate Characteristics**

### **Series 51-SY5000**

				Flow-rate characteristics Note)							
Valve model	T	ype of actuation	Port size	1→4/2 (P→A/B)			4/2-	4/2→5/3 (A/B→EA/EB)			
			C(dm <sup>3</sup> /(s·bar))	b	Cv	C(dm <sup>3</sup> /(s·bar))	b	Cv			
	2-	Single		2.4	0.44	0.64	2.8	0.00	0.66		
po	position	Double		2.4	0.41	0.64	2.0	0.29	0.00		
54 OV5 - 40 -		Closed center		1.8	0.47	0.50	1.8	0.40	0.47		
51-SY5□40-□ -02	3- position	Exhaust center	1/4	1.4	0.55	0.44	3.0 [1.2]	0.33 [0.48]	0.72 [0.37]		
	position	Pressure center		3.3 [0.84]	0.36 [0.60]	0.85 [0.28]	1.8	0.40	0.48		



### **Series 51-SY7000**

				Flow-rate characteristics Note)							
Valve model	T	ype of actuation	Port size	-	1→4/2 (P→A/B)			4/2→5/3 (A/B→EA/EB)			
				C(dm <sup>3</sup> /(s·bar))	b	Cv	C(dm <sup>3</sup> /(s·bar))	b	Cv		
	2-	Single		4.1	0.41	1.1	4.1	0.29	1.0		
	position	Double		4.1	0.41	1.1	4.1	0.29	1.0		
54 OV7 - 40 -		Closed center		3.0	0.43	0.80	2.6	0.41	0.72		
51-SY7□40-□ -02	3- position	Exhaust center	1/4	2.6	0.42	0.71	4.7 [1.7]	0.35 [0.48]	1.1 [0.49]		
	position	Pressure center		5.3 [2.3]	0.39 [0.49]	1.3 [0.65] 2.2	2.2	0.49	0.63		
2- positio	2- position	Single Double		4.9	0.29	1.2	4.5	0.27	1.1		
54 OV5540 5		Closed center	1	3.0	0.40	0.80	2.6	0.45	0.73		
51-SY7□40-□ -03	3- position	Exhaust center	3/8	2.6	0.42	0.71	4.8 [1.7]	0.35 [0.48]	1.1 [0.49]		
	position	Pressure center		5.3 [2.3]	0.31 [0.51]	1.3 [0.64]	2.3	0.45	0.66		



### **Series 51-SY9000**


		Flow-rate characteristics							
Valve model	Type of actuation		Port size	1→4/2 (P→A/B)			4/2→5/3 (A/B→EA/EB)		
				C(dm <sup>3</sup> /(s·bar))	b	Cv	C(dm <sup>3</sup> /(s·bar))	b	Cv
51-SY9□40-□	2-	Single	3/8	7.9	0.34	2.0	9.6	0.43	2.6
-03	position	Double	3/6	7.9	0.34	2.0	9.0	0.43	2.0
51-SY9□40-□	2-	Single	1/2	8.0	0.48	2.2	10	0.29	2.5
-04	position	Double	1/2	/2 8.0	0.48	2.2	10	0.29	2.5




### Construction

### **Series SY**









Symbol 3-position closed center


5 1 3 (EA)(P)(EB) 3-position exhaust center



3-position pressure center



### 3-position closed center/exhaust center/pressure center



(This figure shows a closed center type.)

### **Component Parts**

CUI	iiponent i arts		
No.	Description	Material	Note
1	Body	Aluminum die-casted	White
2	Adapter plate	Resin	White (51-SY9000: Gray)
3	End plate	Resin	White
4	Piston	Resin	_
5	Spool valve assembly	Aluminum, HNBR	_

### **Replacement Parts**

No.	Description		Note		
INO.	Description	51-SY5□40 51-SY7□40 51-SY9□		51-SY9□40	Note
6	Sub-plate	SY5000-27-1*	1/4: SY7000-27-1 * 3/8: SY7000-27-2 *	3/8: SY9000-27-1 * 1/2: SY9000-27-2 *	Aluminum die-casted
7	Gasket	SY5000-11-15	SY7000-11-11	SY9000-11-2	HNBR
_	Round head combination screw	M3 x 26	M4 x 31	SY9000-18-2 (M3 x 42)	For valve mounting (Flat nickel plated)

⚠ Caution
Mounting screw tightening torques
tightening torques
M3: 0.8 N⋅m

M4: 1.4 N·m




<sup>\*</sup> Thread type

# Base Mounted Series 51-SY5000/7000/9000


### Dimensions: 51-SY5000

2-position single L-type plug connector (L) 51-SY5140(R)-□L□□-02□ 60.3 37.2 2 x ø4.3 48 8.3 (For mounting) 15.5 M5 x 0.8 15.5 (External pilot port) Insulator: Black (-) A 8 ⊗ 35  $\otimes$ Insulator: Red (+) ΕA Р Manual 17 override 56 4.3 62.5 65 M5 x 0.8 109.1 (Pilot EXH port) <For external pilot type> L (Lead wire length) 0.3 mm<sup>2</sup> ø1.55 18 18 28 5 x 1/4" (Piping port)

# L-type plug connector with cover (LL) 51-SY5140(R)-□LL□□-02□




# With IP65 compliant cable (TT) 51-SY5140(R)-□TT□□-02□







### Dimensions: 51-SY5000



# L-type plug connector with cover (LL) 51-SY5240(R)-□LL□□-02□




# With IP65 compliant cable (TT) 51-SY5240(R)-□TT□□-02□




# Base Mounted Series 51-SY5000/7000/9000

### Dimensions: 51-SY5000




### L-type plug connector with cover (LL)

### 51-SY5<sup>3</sup>/<sub>4</sub>40(R)-□LL□□-02□




### With IP65 compliant cable (TT)



### Dimensions: 51-SY7000

### 2-position single L-type plug connector (L) 51-SY7140(R)-□L□□-%□ 79.2 10.4 41.7 61 21.5 2 x ø4.3 M5 x 0.8 (For mounting) (External pilot port) Insulator: Black (-) 23 38 46 Insulator: Red (+) Manual EA EA override 21 6.4 21.5 69 67.2 123.3 M5 x 0.8 (Pilot EXH port) <For external pilot type> 71.2 (E-type) L (Lead wire length) 0.3 mm<sup>2</sup> 26.5 20.5 20.5

# L-type plug connector with cover (LL) 51-SY7140(R)-□LL□□-03 □




33

5 x 3/8", 1/4"


(Piping port)

# With IP65 compliant cable (TT) 51-SY7140(R)- $\Box$ TT $\Box$ - $_{03}^{02}$ $\Box$




# Base Mounted Series 51-SY5000/7000/9000

### Dimensions: 51-SY7000




### L-type plug connector with cover (LL)


### 51-SY7240(R)-□LL□□-%3□



# With IP65 compliant cable (TT) 51-SY7240(R)- $\Box$ TT $\Box$ - $\Box$ - $\Box$ - $\Box$ 2




### Dimensions: 51-SY7000




### L-type plug connector with cover (LL)

### 51-SY7<sup>3</sup>/<sub>4</sub>40(R)-□LL□□-<sup>02</sup>/<sub>93</sub>□




### With IP65 compliant cable (TT)




# Base Mounted Series 51-SY5000/7000/9000


### Dimensions: 51-SY9000



# L-type plug connector with cover (LL) 51-SY9140- $\square$ LL $\square$ - $^{03}_{04}\square$




# With IP65 compliant cable (TT) 51-SY9140- $\square$ TT $\square$ $\square$ - $^{03}_{04}$ $\square$






### Dimensions: 51-SY9000




### L-type plug connector with cover (LL)

### 51-SY9240-□LL□□-%2□



# With IP65 compliant cable (TT) 51-SY9240-□TT□□-<sup>03</sup>/<sub>04</sub>□




**SMC** 



# Type **20**

# Intrinsically Safe Explosion-proof System 5 Port Solenoid Valve Series 51-SY5000/7000 Body Ported Manifold Bar Stock Type


### **How to Order Manifold**



NPTF


00T

### **How to Order Valve Manifold Assembly**



# Body Ported Series 51-SY5000/7000

### **How to Order Valve**



### Electrical entry

20

30

100

2000 mm

3000 mm

10000 mm

	Electrical entry •
Symbol	Electrical entry
L	L-type plug connector
LL	L-type plug connector with cover
TT Note)	With IP65 compliant cable Ground nut

Note) TT-type is connected to the terminal block. Cables other than the connected one cannot be used.




Note) When placing an order for body ported solenoid valve as a single unit, mounting screws and a gasket for manifold are not attached. Order them separately, if necessary. (For details, refer to page 32.)

Semi-standard



# Series 51-SY5000/7000




### **Manifold Specifications**

	Model	51-SS5Y5-20	51-SS5Y7-20			
Арр	licable valve	51-SY5□20	51-SY7□20			
Manifold t	уре	Single bas	se B mount			
P (SUP)/R	(EXH)	Common	SUP/EXH			
Valve stat	ions	2 to 20 sta	ations Note 1)			
A, B port I	ocation	Valve				
	P, EA, EB port	1/4				
Port size A, B port		1/8 C4 (ø4 one-touch fitting) C6 (ø6 one-touch fitting) C8 (ø8 one-touch fitting)	1/4 C8 (ø8 one-touch fitting) C10 (ø10 one-touch fitting)			
Manifold base mass W (g) n: Stations		W = 36n + 64	W = 43n + 64			

No

### **Flow-rate Characteristics**

	Port	size	Flow-rate characteristics								
Model	1, 5, 3	4, 2	1→	4/2 (P→A	/B)	4/2→5/3 (A/B→EA/EB)					
	(P, EA, EB)	(A, B)	C [dm <sup>3</sup> /(s·bar)]	b	Cv	C [dm³/(s·bar)]	b	Cv			
51-SS5Y5-20	1/4	C8	1.9	0.28	0.48	2.2	0.20	0.53			
51-SS5Y7-20	1/4	C10	3.6	0.31	0.93	3.6	0.27	0.88			





Note 1) For 10 stations or more (5 stations or more for the 51-SS5Y7), supply pressure to P port on both sides and exhaust from EA/EB port on both sides.


Note 2) Refer to "Manifold Options" on page 32.


**Marning** If a resin tube is used, take measures against static electricity. ⚠

# Body Ported *Series* 51-SY5000/7000


### Dimensions: 51-SY5000

# L-type plug connector (L) 51-SS5Y5-20-Stations -□









With IP65 compliant cable (TT) 51-SS5Y5-20-Stations - □


Max.10	177
39	L (Lead wire length)


Stations n	2 stations	3 stations	4 stations	5 stations	6 stations	7 stations	8 stations	9 stations	10 stations	11 stations	12 stations	13 stations	14 stations	15 stations	16 stations	17 stations	18 stations	19 stations	20 stations
L1	60	76	92	108	124	140	156	172	188	204	220	236	252	268	284	300	316	332	348
L2	40	56	72	88	104	120	136	152	168	184	200	216	232	248	264	280	296	312	328

# Series 51-SY5000/7000


### **Dimensions: 51-SY7000**


# L-type plug connector (L) 51-SS5Y7-20-Stations -□





### L-type plug connector with cover (LL)






Stations r	2 stations	3 stations	4 stations	5 stations	6 stations	7 stations	8 stations	9 stations	10 stations	11 stations	12 stations	13 stations	14 stations	15 stations	16 stations	17 stations	18 stations	19 stations	20 stations
L1	55	74	93	112	131	150	169	188	207	226	245	264	283	302	321	340	359	378	397
L2	46	65	84	103	122	141	160	179	198	217	236	255	274	293	312	331	350	369	388


### **Manifold Options**

# ■ Type 20 Blanking Plate Assembly



Series	Assembly part no.
51-SY5000	SY5000-26-20A
51-SY7000	SY7000-26-22A


### ■ Gasket Assembly Part No.



Series	Gasket assembly
51-SY5000	SY5000-GS-1
51-SY7000	SY7000-GS-1

Note) Gasket assembly consists of 10 sets of mounting screws and a gasket.

### ■ Individual SUP Spacer Assembly




Series	Assembly part no.	Port size	t
51-SY5000	SY5000-38-1*A	1/8	15
51-SY7000	SY7000-38-1*A	1/4	18




Note) The SUP port of the 51-SY5000/7000 may be either on the lead wire side or on the end plate side. (An assembly is shipped under the conditions shown in the figure.)

# ■ Individual EXH Spacer Assembly



Series	Assembly part no.	Port size	t
51-SY5000	SY5000-39-1*A	1/8	15
51-SY7000	SY7000-39-1*A	1/4	18

### ■ Individual SUP Spacer Assembly + Individual EXH Spacer Assembly (Double spacer)



Series	Individual SUP + Individual EXH assembly part no.	Port size	Applicable manifold type	
51-SY5000	SY5000-75-2*A	1/8	Turno 20	
51-SY7000	SY7000-73-3*A	1/4	Type 20	

O No

Note) The SUP spacer's port does not have an orientation. As for the EXH ports, adjust the symbol "5" to the pilot valve side. Also, please make sure to connect the individual ports to protect the wiring section of the pilot valve from drainage, etc.

The individual SUP spacer and EXH spacer can be mounted either on the upper side or lower side. (The above illustration shows the condition when the product is shipped out from a factory already assembled.)



Mounting screw tightening torques

M3: 0.8 N·m M4: 1.4 N·m

Thread type				
Nil	Rc			
F	G			
N	NPT			
Т	NPTF			

### **⚠** Warning


When mounting a valve or spacer on the manifold base or sub-plate, etc., those mounting directions are determined. If mounted in the wrong direction, the equipment to be connected may cause malfunction. Refer to external dimensions, and then mount it.




# **Intrinsically Safe Explosion-proof System** 5 Port Solenoid Valve Series 51-SY5000/7000 **Base Mounted Manifold Bar Stock Type**

### **How to Order Manifold**


### **How to Order Valve Manifold Assembly**





Type 42/External Pilot Capable

ø5/16" one-touch fitting



One-touch fitting (Metric size)

**⚠** Warning Applicable series Symbol Port size ø6 one-touch fitting 51-SY5000 ø8 one-touch fitting 51-SY7000 ø10 one-touch fitting

51-SY5000

If a resin tube is used, take measures against static electricity.

N

NPT


NPTF

One-touch fitting (Inch size)

Symbol	Port size	Applicable series	
N7	ø1/4" one-touch fitting	51-SY5000	
N9	ø5/16" one-touch fitting		
N11	ø3/8" one-touch fitting	51-SY7000	

## Base Mounted Series 51-SY5000/7000

### **How to Order Valve**




valve have an SMC model certification label with a model certification number listed on it. Be sure to use only a barrier and a valve whose numbers match. · If an SMC model certification label has not been stuck on the product, or if the model certification numbers do not match, the product cannot be said to be an intrinsically safe explosion-proof system. Therefore, be sure to use only a barrier

purchased from SMC.

Cables other than the connected one cannot be used.



## Series 51-SY5000/7000



## **Manifold Specifications**


1	Model		51-SS5Y5-41	51-SS5Y5-42	51-SS5Y7-42	
Applicable valve			51-SY	<b>′</b> 5□40	51-SY7□40	
Manifold type			:	Single base B moun	t	
P (SUP)/R (EXH)				Common SUP/EXH		
Valve static	ns			2 to 20 stations Note 1	)	
A, B port		Location	Base			
location		Direction				
	P, E	A, EB port		1/4		
Port size A, B port		1/8 C6 (ø6 one-touch fitting) C8 (ø8 one-touch fitting)	1/4 C6 (ø6 one-touch fitting) C8 (ø8 one-touch fitting)	1/4 C10 (ø10 one- touch fitting)		
Manifold base mass W (g) n: Stations		W =61n + 101	W =79n + 127	W =100n + 151		



Note 1) For 10 stations or more (5 stations or more for the 51-SS5Y7), supply pressure to P port on both sides and exhaust from EA/EB port on both sides.

## **Flow-rate Characteristics**

	Port	size		Flo	ow-rate ch	aracteristi	cs	
Model	1, 5, 3		1→	4/2 (P→A	/B)	4/2→5/3 (A/B→EA/EB)		
	(P, EA, EB)	(P, EA, EB) (A, B)		b	Cv	C [dm <sup>3</sup> /(s·bar)]	b	Cv
51-SS5Y5-41	1/4	C8	1.8	0.23	0.44	1.9	0.16	0.45
51-SS5Y5-42	1/4	C8	1.9	0.20	0.46	1.9	0.12	0.43
51-SS5Y7-42	1/4	C10	3.0	0.25	0.75	3.0	0.12	0.66







Note 2) Refer to "Manifold Options" on page 39.

## Base Mounted Series 51-SY5000/7000

## Dimensions: 51-SY5000






## Series 51-SY5000/7000

## **Dimensions: 51-SY5000**

L-type plug connector (L) 51-SS5Y5-42-Stations - □ □ 82.3 (E-type) (Lead wire length) A M5 x 0.8 (Pilot EXH port) <When using external pilot Manual override solenoid valve> 109.7 24 20 65.4 156 23.6 20 39 29 6 x 1/4" 33.7 46.3 {P(1), EA(5), EB(3) port} M5 x 0.8 (External pilot port) (Pitch) P = 17.5L2 L1 Stations 1 2----n 47.5 53 27.3 38



2n x 1/4"

{A(4), B(2) port}


(Pitch)


19

Stations n	2 stations	3 stations	4 stations	5 stations	6 stations	7 stations	8 stations	9stations	10 stations	11 stations	12 stations	13 stations	14 stations	15 stations	16 stations	17 stations	18 stations	19 stations	20 stations
L1	59.5	77	94.5	112	129.5	147	164.5	182	199.5	217	234.5	252	269.5	287	304.5	322	339.5	357	374.5
L2	49.5	67	84.5	102	119.5	137	154.5	172	189.5	207	224.5	242	259.5	277	294.5	312	329.5	347	364.5

## Base Mounted Series 51-SY5000/7000

## Dimensions: 51-SY7000





Stations n	2 stations	3 stations	4 stations	5 stations	6 stations	7 stations	8 stations	9 stations	10 stations	11 stations	12 stations	13 stations	14 stations	15 stations	16 stations	17 stations	18 stations	19 stations	20 stations
L1	61	80	99	118	137	156	175	194	213	232	251	270	289	308	327	346	365	384	403
L2	49	68	87	106	125	144	163	182	201	220	239	258	277	296	315	334	353	372	391

## Series 51-SY5000/7000


## **Manifold Options**

## ■ Type 41, 42 Blanking Plate Assembly



Series	Assembly part no.
51-SY5000	SY5000-26-20A
51-SY7000	SY7000-26-22A


## ■ Gasket Assembly Part No.



Series	Gasket assembly
51-SY5000	SY5000-GS-2
51-SY7000	SY7000-GS-2

Note) Gasket assembly consists of 10 sets of mounting screws and a gasket.


## ■ Individual SUP Spacer Assembly



Series	Assembly part no.	Port size	t
51-SY5000	SY5000-38-16*A	1/8	15
51-SY7000	SY7000-38-16*A	1/4	18


Note) The SUP port of the 51-SY5000/7000 may be either on the lead wire side or on the end plate side. (An assembly is shipped under the conditions shown in the figure.)

## ■ Individual EXH Spacer Assembly



Series	Assembly part no.	Port size	t
51-SY5000	SY5000-39-16*A	1/8	15
51-SY7000	SY7000-39-16*A	1/4	18

## ■ Individual SUP Spacer Assembly + Individual EXH Spacer Assembly (Double spacer)



Series	Individual SUP + Individual EXH assembly part no.	Port size
51-SY5000	SY5000-75-1*A	1/8
51-SY7000	SY7000-73-1*A	1/4

Note)

Note) The port on a spacer can be directed to the pilot valve side or end plate side. For mounting the port to the pilot valve side, please make sure to connect the ports to protect the pilot valve wiring section from drainage.

The individual SUP spacer and EXH spacer can be mounted either on the upper side or lower side. (The above illustration shows the condition when the product is shipped out from a factory already assembled.)

<u> </u>	Caution
Moi	inting screw

Mounting screw tightening torques

M3: 0.8 N·m M4: 1.4 N·m

*	Thre	ad ty	/pe
	NI:I	О.	

	•••• • <b>)</b>
Nil	Rc
F	G
N	NPT
Т	NPTF


## **Marning**

When mounting a valve or spacer on the manifold base or sub-plate, etc., those mounting directions are determined. If mounted in the wrong direction, the equipment to be connected may cause malfunction. Refer to external dimensions, and then mount it.




## Series 51-SY

## **Zener Diode Barrier Dimensions**



## **∴** Caution


Terminal No. 2, No. 7 and the DIN rail mounting bracket on the bottom part of the barrier or terminal for grounding are short circuit connected.



Internal circuit diagram

# Series 51-SY Insulating Barrier Dimensions

#### 51-SYE100-F



## **⚠** Caution

For this product, the barrier and the valve as a set are certified as a system, so please be aware of the following.

- For this product, both the barrier and the valve have an SMC model certification label with a model certification number listed on it. Be sure to use only a barrier and a valve whose numbers match.
- · If an SMC model certification label has not been stuck on the product, or if the model certification numbers do not match, the product cannot be said to be an intrinsically safe explosion-proof system. Therefore, be sure to use only a barrier purchased from SMC.





## Safety Instructions

These safety instructions are intended to prevent hazardous situations and/or equipment damage. These instructions indicate the level of potential hazard with the labels of "Caution," "Warning" or "Danger." They are all important notes for safety and must be followed in addition to International Standards (ISO/IEC)\*1), and other safety regulations.

\*1) ISO 4414: Pneumatic fluid power – General rules relating to systems.

ISO 4413: Hydraulic fluid power – General rules relating to systems.

IEC 60204-1: Safety of machinery - Electrical equipment of machines. (Part 1: General requirements)

ISO 10218-1: Manipulating industrial robots - Safety.

etc.

**⚠** Caution:

Caution indicates a hazard with a low level of risk which, if not avoided, could result in minor or

moderate injury.

**⚠** Warning:

Warning indicates a hazard with a medium level of risk which, if not avoided, could result in death or

serious injury.

⚠ Danger :

Danger indicates a hazard with a high level of risk which, if not avoided, will result in death or serious

injury.

## **Marning**

1. The compatibility of the product is the responsibility of the person who designs the equipment or decides its specifications.

Since the product specified here is used under various operating conditions, its compatibility with specific equipment must be decided by the person who designs the equipment or decides its specifications based on necessary analysis and test results. The expected performance and safety assurance of the equipment will be the responsibility of the person who has determined its compatibility with the product. This person should also continuously review all specifications of the product referring to its latest catalog information, with a view to giving due consideration to any possibility of equipment failure when configuring the equipment.

2. Only personnel with appropriate training should operate machinery and equipment.

The product specified here may become unsafe if handled incorrectly. The assembly, operation and maintenance of machines or equipment including our products must be performed by an operator who is appropriately trained and experienced.

- 3. Do not service or attempt to remove product and machinery/equipment until safety is confirmed.
  - 1. The inspection and maintenance of machinery/equipment should only be performed after measures to prevent falling or runaway of the driven objects have been confirmed.
  - 2. When the product is to be removed, confirm that the safety measures as mentioned above are implemented and the power from any appropriate source is cut, and read and understand the specific product precautions of all relevant products carefully.
  - 3. Before machinery/equipment is restarted, take measures to prevent unexpected operation and malfunction.
- 4. Contact SMC beforehand and take special consideration of safety measures if the product is to be used in any of the following conditions.
  - 1. Conditions and environments outside of the given specifications, or use outdoors or in a place exposed to direct sunlight.
  - 2. Installation on equipment in conjunction with atomic energy, railways, air navigation, space, shipping, vehicles, military, medical treatment, combustion and recreation, or equipment in contact with food and beverages, emergency stop circuits, clutch and brake circuits in press applications, safety equipment or other applications unsuitable for the standard specifications described in the product catalog.
  - 3. An application which could have negative effects on people, property, or animals requiring special safety analysis.
  - 4. Use in an interlock circuit, which requires the provision of double interlock for possible failure by using a mechanical protective function, and periodical checks to confirm proper operation.





## **⚠** Caution

1. The product is provided for use in manufacturing industries.

The product herein described is basically provided for peaceful use in manufacturing industries.

If considering using the product in other industries, consult SMC beforehand and exchange specifications or a contract if necessary.

If anything is unclear, contact your nearest sales branch.

## Limited warranty and Disclaimer/Compliance Requirements

The product used is subject to the following "Limited warranty and Disclaimer" and "Compliance Requirements". Read and accept them before using the product.

## **Limited warranty and Disclaimer**

- 1. The warranty period of the product is 1 year in service or 1.5 years after the product is delivered.\*2) Also, the product may have specified durability, running distance or replacement parts. Please consult your nearest sales branch.
- 2. For any failure or damage reported within the warranty period which is clearly our responsibility, a replacement product or necessary parts will be provided.
  - This limited warranty applies only to our product independently, and not to any other damage incurred due to the failure of the product.
- 3. Prior to using SMC products, please read and understand the warranty terms and disclaimers noted in the specified catalog for the particular products.
  - \*2) Vacuum pads are excluded from this 1 year warranty.

A vacuum pad is a consumable part, so it is warranted for a year after it is delivered.

Also, even within the warranty period, the wear of a product due to the use of the vacuum pad or failure due to the deterioration of rubber material are not covered by the limited warranty.

## **Compliance Requirements**

- 1. The use of SMC products with production equipment for the manufacture of weapons of mass destruction (WMD) or any other weapon is strictly prohibited.
- 2. The exports of SMC products or technology from one country to another are governed by the relevant security laws and regulations of the countries involved in the transaction. Prior to the shipment of a SMC product to another country, assure that all local rules governing that export are known and followed.





Be sure to read before handling.


Refer to back pages 1 and 2 for Safety Instructions, "Handling Precautions for SMC Products" (M-E03-3) for 3/4/5 Port Solenoid Valves Precautions.

#### **Manual Override**

## **Marning**


#### ■ Non-locking push type [Standard]

Press in the direction of the arrow.



#### ■ Push-turn locking slotted type [Type D]

While pressing, turn in the direction of the arrow. If it is not turned, it can be operated the same way as the non-locking type.




#### 

When operating the locking type D with a screwdriver, turn it gently using a watchmaker's screwdriver. [Torque: Less than  $0.1 \text{ N} \cdot \text{m}$ ]

#### ■ Push-turn locking lever type [Type E]

While pressing, turn it the direction of the arrow. If it is not turned, it can be operated the same way as the non-locking type.



#### **⚠** Caution

When locking the manual override on the push-turn locking types (D, E), be sure to push it down before turning. Turning without first pushing it down can cause damage to the manual override and trouble such as air leakage, etc.

#### **Exhaust Side**

## **⚠** Caution

The 51-SY series pilot valve and main valve share a common exhaust inside the valve. Therefore, do not block the exhaust port when arranging the piping.

### Series 51-SY5000/7000/9000 Used as a 3-Port Valve

## **⚠** Caution

### In case of using a 5-port valve as a 3-port valve

The 51-SY5000/7000/9000 series can be used as normally closed (N.C.) or normally open (N.O.) 3-port port valves by closing one of the cylinder ports (A or B) with a plug. However, they should be used with the exhaust ports kept open.


F	Plug position		B port	A port
Typ	Type of actuation		N.C.	N.O.
Number of solenoids	Solenoids	ngle	Plug (A) (B) (EA) (P) (EB)	Plug (A) (B) 2  T
		ouble	Plug (A) (B) (EA) (P) (EB)	Plug (A) (B) (

#### **How to Use Plug Connector**

## **∧** Caution

#### 1. Attaching and detaching connectors

- To attach a connector, hold the lever and connector unit between your fingers and insert straight onto the pins of the solenoid valve so that the lever's pawl is pushed into the groove and locks.
- To detach a connector, remove the pawl from the groove by pushing the lever downward with your thumb, and pull the connector straight out.











Be sure to read before handling.

Refer to back pages 1 and 2 for Safety Instructions, "Handling Precautions for SMC Products" (M-E03-3) for 3/4/5 Port Solenoid Valves Precautions.

#### **One-touch Fittings**

## **Marning**

 Please take antistatic precautions appropriate to the use of resin tubing.

Refer to "Recommended Practices for Explosion-Protected Electrical Installations in General Industries" issued by Technology Institution of Industrial Safety.

## **⚠** Caution

The pitch determined for each of the 51-SY series piping ports (P, A, B, etc.) is based on the assumption that KJ series one-touch fittings will be used.

For this reason, other pipe fittings may interfere with each other depending on their type and size. Dimensions should be confirmed in a pipe fitting catalog before they are used.

## • Tubing attachment/detachment for one-touch fittings

#### 1) Attaching of tubing

- 1. Take a tubing having no flaws on its periphery and cut it off at a right angle. When cutting the tubing, use tubing cutters TK-1, 2 or 3. Do not use pinchers, nippers or scissors, etc. If cutting is done with tools other than tubing cutters, the tubing may be cut diagonally or become flattened, etc., making a secure installation impossible, and causing problems such as the tubing pulling out after installation or air leakage. Allow some extra length in the tubing.
- Grasp the tubing and push it in slowly, inserting it securely all the way into the fitting.
- After inserting the tubing, pull on it lightly to confirm that it will not come out. If it is not installed securely all the way into the fitting, this can cause problems such as air leakage or the tubing pulling out.

#### 2) Detaching of tubing

- 1. Push in the release button sufficiently, pushing its collar equally around the circumference.
- Pull out the tubing while holding down the release button so that it does not come out. If the release button is not pressed down sufficiently, there will be increased bite on the tubing and it will become more difficult to pull it out.
- When the removed tubing is to be used again, cut off the portion which has been chewed before reusing it. If the chewed portion of the tubing is used as is, this can cause trouble such as air leakage or difficulty in removing the tubing.
- The pitch determined for each of the 51-SY series piping ports (A, B, etc.) is based on the assumption that KJ series onetouch fittings will be used. For this reason, other pipe fittings may interfere with each other depending on their type and size. Dimensions should be confirmed in a pipe fitting catalog before they are used.

#### **Other Tubing Brands**

## **⚠** Caution

 When using other than SMC brand tubing, confirm that the following specifications are satisfied with respect to the outside diameter tolerance of the tubing.

1) Nylon tubing
2) Soft nylon tubing
3) Polyurethane tubing
within ±0.1 mm
within ±0.1 mm
within +0.15 mm,
within -0.2 mm.

Do not use tubing which do not meet these outside diameter tolerances. It may not be possible to connect them, or they may cause other trouble, such as air leakage or the tubing pulling out after connection.

### **Solenoid Valve Mounting**

## **⚠** Caution

Mount it so that there is no slippage or deformation in gaskets, and tighten with the tightening torque as shown below.

Model	Thread size	Tightening torque
51-SY5000	М3	0.8 N⋅m
51-SY7000	M4	1.4 N⋅m
51-SY9000	МЗ	0.8 N⋅m





Be sure to read before handling.

Refer to back pages 1 and 2 for Safety Instructions, "Handling Precautions for SMC Products" (M-E03-3) for 3/4/5 Port Solenoid Valves Precautions.

#### **Valve Selection for Hazardous Environment**



The explosion-proof performance of the 51-SY (intrinsically safe explosion-proof system) is ExiaIIBT4 (See the reference "Explosion-proof Structure Symbol (ExiaIIBT4)"). Selection of a valve for a dangerous place should be done in accordance with "Recommended Practices for Explosion-Protected Electrical Installations in General Industries" issued by Technology Institution of Industrial Safety.

#### **Classification of Hazardous Environment**

## **⚠** Warning

This valve should be used in a class-1 or class-2 environment by combining with a barrier (placed in non-hazardous location).

Note that this valve can not be used in a class-0 environment.

#### Classification of hazardous environment

#### ■ Class-0 environment ...... Not available

A place where an explosive atmosphere is constantly generated or can be generated.

Also, a place where atmosphere is above the lower limit of explosion constantly or for a long time of period is also regarded as the class-0 environment for safety season.

#### (Places often falling into the class-0 environment)

- a) A container of flammable liquid or space above the liquid level in the container.
- b) Around the liquid level of flammable liquid in an open container or similar place.

#### ■ Class-1 environment ..... Available

A place where an explosive atmosphere can be generated periodically or occasionally.

Also, a place which can have a dangerous concentration of explosive gas due to repair, maintenance, or leakage.

#### (Places often falling into the class-1 environment)

- a) Around an opening which releases explosive gas due to removal of a product during normal operation, opening/closing of a lid, or operation of a safety valve.
- b) Around the opening of a container such as a tanker and drum which is filled with flammable liquid.
- Around an opening which releases explosive gas due to occasional operation of a relief valve.
- d) Around the opening of a gas-vent on a tank etc.
- e) Around an opening which releases explosive gas during inspection or repair work.
- f) A room or a place which can have explosive gas due to insufficient ventilation.
- g) The part which is above the roof of a floating roof tank but within the shell.
- A place which can have leaked explosive gas and can accumulate the gas such as a pit.

#### ■ Class-2 environment ..... Available

A place where explosive atmosphere can be generated under abnormal condition though an explosive atmosphere cannot be generated under normal condition.

- A place where flammable gas is constantly operated, but it is enclosed in an air-tight container or facility, and concentration of the gas may be thick when the container or facility gets broken due to an accident or when operation fails.
- A place that can have a dangerous explosive gas concentration due to the breakage of mechanical ventilation equipment though the equipment is usually reliable.

#### (Places often falling into the class-2 environment)

- a) A place where dangerous gas or liquid can leak from a container if the container is corroded.
- b) A place where dangerous gas or liquid can be released or leak out due to incorrect operation of equipment or an abnormal reaction of equipment after exposure to high temperature and high pressure.
- A place where a dangerous atmosphere is generated due to failure of mandatory ventilation equipment and stagnation of explosive gas.
- d) A place which is indoors around or next to the class-1 environment and rarely has explosive gas with dangerous concentration.

#### **Prohibition of Disassembly and Modification**

## **Marning**

Disassembling the pilot valve and barrier can deteriorate the explosion-proof performance, and it may lead to an accident.

Therefore, please do not disassemble or modify the pilot valve and barrier.

### **Intrinsically Safe Explosion-proof Circuit Wiring**

## **⚠** Warning

Wiring of intrinsically safe explosion-proof circuits should not be routed with the other circuits. Also, it should not have electrostatic induction or electromagnetic induction.






Be sure to read before handling.

Refer to back pages 1 and 2 for Safety Instructions, "Handling Precautions for SMC Products" (M-E03-3) for 3/4/5 Port Solenoid Valves Precautions.

#### Reference

#### **Explosion-proof Structure Symbol (ExialIBT4)**

#### **Symbols Specified by Technical Standard**



(1) Groups of explosion-proof equipment

Explosion-proof equipment is classified into two groups depending on the place where electric equipment is used.

Group I: Electric equipment which is used in a dangerous environment within a tunnel or mine

Group II: Electric equipment which is used in a dangerous environment within a factory or office.

SMC valve belongs to Group II.

(2) Classification of gas

Classification of gas corresponds to the explosion class of gas specified in the conventional standard, and there are three classes, A, B, and C, depending on the characteristics of explosive gas. The classification of gas specifies the dangerous degree as C>B>A. SMC valve is applicable to the gases classified into A and B.

(3) Temperature class

Temperature class corresponds to the ignition degree of gas specified in the conventional standard, and there are six classes, T1 to T6. T1 is the least dangerous gas which has the highest ignition temperature, and T6 is the most dangerous gas which has the lowest ignition temperature. SMC valve is applicable to T1 to T4 temperature classes.



## Record of changes

- Edition B \* Deleted the system "C" and "E" from How to Order on page 1, 14, 28, 34.
  - \* Deleted the 51-SYE100-C from Zener Diode Barrier Dimensions on page 41.
  - \* Deleted the 51-SYE100-E from Insulating Barrier Dimensions on page 42.

NQ